

WWW.ALDDATASHEET.COM

Part Name Description

50R-028

ROTARY ATTENUATOR (1 Page)



JFW

100%



1 page

SPECIFICATION SHEET
JFW MODEL 50R-028
ROTARY ATTENUATOR

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

Frequency Range	DC-1000 MHz
Impedance	50 Ohms nominal
Attenuation Range	0-1 dB in 0.1 dB steps
VSWR	1.2:1 maximum
Insertion Loss	1 dB maximum
Attenuation Accuracy	± 0.03 dB DC-500 MHz ± 0.05 dB 500-1000 MHz
RF Input Power	2 Watts average
Direction of Rotation	Attenuation increases in a Clockwise direction
Indexing	30 degrees with stops at Minimum and maximum
RF Connector	BNC, TNC, N or SMA female
Operating Temperature Range	-20°C to +85°C
Physical Size	See outline drawings 092-039 (SMA) 092-427 (BNC) 092-6194 (N/SMA) 092-049-01 (BNC/SMA) 092-049-02 (TNC/SMA)

Link URL<http://html.alldatasheet.com/html-pdf/335609/JFW/50R-028/54/1/50R-028.html>**Sponsor of Alldatasheet****IC5858**

Chinese Marketplace to Buy/Sell Semiconductor Electronic components on-line for Brokers and Distributors.
IC5858.com

ICPART.com

Korean Buy/Sell Semiconductor & Electronic components on-line marketplace for Brokers and Distributors.
ICpart.com

Ads by Google

[Search for 2n2907](#)

Find datasheets, specs and suppliers for 2n2907.

octopart.com**ICBAIBAI**

Japanese Buy/Sell Semiconductor & Electronic components on-line marketplace for Brokers and Distributors.
ICBAIBAI.com

IC2IC

World wide Buy/Sell Semiconductor & Electronic components on-line marketplace for Brokers and Distributors.
IC2IC.com

Does ALLDATASHEET help your business so far? [\[DONATE \]](#)